

DIGITAL MULTIMETER SPECIFICATIONS

● DC VOLTAGE

RANGE	RESOLUTION	ACCURACY	OVERVOLTAGE PROTECTION
2V	1mV	$\pm 0.5\%$	500V DC/AC rms
20V	10mV	$\pm 0.8\%$	
200V	100mV	$\pm 0.8\%$	
500V	1V	$\pm 0.8\%$	

● DC CURRENT

RANGE	RESOLUTION	ACCURACY	OVERCURRENT PROTECTION
200mA	0.1mA	$\pm 0.2\%$	200mA FAST

● AC VOLTAGE

RANGE	RESOLUTION	ACCURACY	OVERCURRENT PROTECTION
200V	100mV	$\pm 1.2\%$	500V DC/AC rms
500V	1V	$\pm 1.2\%$	

● RESISTANCE

RANGE	RESOLUTION	ACCURACY	OVERCURRENT PROTECTION
2K Ω	1 Ω	$\pm 1\%$	220V DC/AC rms
20K Ω	10 Ω	$\pm 1\%$	
200K Ω	100 Ω	$\pm 1\%$	
2MK Ω	1K Ω	$\pm 1\%$	

● DIODE AND BUZZER

DISPLAY OF DIODE - RESEMBLING FORWARD CONDUCTION VOLTAGE AND INSIDE BUZZER SHALL ALAR IF TEST RESISTANCE BELOW 50 Ω